AD-A266 746

DOCUMENTATION PAGE

January 1993

Form Approved OMB No. 0704-0188

of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, 1, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this tions for reducing this burden. To Washington Headquarters Services, Directorate for information Operations and Reports, 1215 Jefferson 2202–302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, OC 20503.

2. REPORT DATE

3. REPORT TYPE AND DATES COVERED

Technica:

4. TITLE AND SUBTITLE Logarithmic Asymptotics for Steady-State Tail Probabilities

DAAL03-91-6-010

5. FUNDING NUMBERS

6. AUTHOR(S)

Peter W. Glynn and Ward Whitt

in a Single-Server Oueue

7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)

Department of Operations Research Terman Engineering Center Stanford University

8. PERFORMING ORGANIZATION REPORT NUMBER

93 - 1

9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)

U. S. Army Research Office

Stanford, CA 94305-4022

P. O. Box 12211

Research Triangle Park, NC 27709-2211

10. SPONSORING / MONITORING AGENCY REPORT NUMBER

ARD 28809.13-MASDI

11. SUPPLEMENTARY NOTES

The view, opinions and/or findings contained in this report are those of the author(s) and should not be construed as an official Department of the Army position, policy, or decision, unless so designated by other documentation.

12a. DISTRIBUTION / AVAILABILITY STATEMENT

12b. DISTRIBUTION CODE

Approved for public release; distribution unlimited.

13. ABSTRACT (Maximum 200 words)

Please see reverse side

93 7 08 07,7

high speed networks, asynchronous transfer mode, single-server queue, waiting time, workload, tail probabilities, small-tail asymptotics, large deviations, cumulant generating functions, counting process, effective bandwidths, admission

15. NUMBER OF PAGES 40

16. PRICE CODE

17. SECURITY CLASSIFICATION OF REPORT

18. SECURITY CLASSIFICATION OF THIS PAGE

19. SECURITY CLASSIFICATION OF ABSTRACT

20. LIMITATION OF ABSTRACT

UNCLASSIFIED

UNCLASSIFIED

UNCLASSIFIED

UL

Standard Form 298 (Rev. 2-89)

NSN 7540-01-280-5500

Abstract. We consider the standard single-server queue with unlimited waiting space and the first-in first-out service discipline. We find conditions for the steady-state waiting-time distribution to have small-tail asymptotics of the form

$$x^{-1} \log P(W > x) \rightarrow -\theta^* \text{ as } x \rightarrow \infty$$

for $\theta^* > 0$. We require only stationarity of the basic sequence of service times minus interarrival times and a Gärtner-Ellis condition for the cumulant generating function of the associated partial sums, i.e., $n^{-1} \log E e^{\theta S_n} \to \psi(\theta)$ as $n \to \infty$, plus regularity conditions on the decay rate function ψ . The asymptotic decay rate θ^* is the root of the equation $\psi(\theta) = 0$. This result in turn implies a corresponding asymptotic result for the steady-state workload in a queue with general nondecreasing input. This asymptotic result covers the case of multiple independent sources, so that it provides additional theoretical support for a concept of effective bandwidths for admission control in emerging high-speed communication networks.

LOGARITHMIC ASYMPTOTICS FOR STEADY-STATE TAIL PROBABILITIES IN A SINGLE-SERVER QUEUE

by

Peter W. GLynn and Ward Whitt

DAIL CANTUL THE TRANSPORTED 9

TECHNICAL REPORT No. 93-1

JANUARY 1993

Prepared under the Auspices of U.S. Army Research Contract DAAL-03-91-G-0101

Acces	ion For	
DTIC	.01- 15d 11	
By Dist is	estica (
	ivaribility Codes	
Dist	Avan en a for Special	
A-1		

Approved for public release: distribution unlimited.

Reproduction in whole or in part is permitted for any purpose of the United States Government

DEPARTMENT OF OPERATIONS RESEARCH STANFORD UNIVERSITY STANFORD, CA 94305

LOGARITHMIC ASYMPTOTICS FOR STEADY-STATE TAIL PROBABILITIES IN A SINGLE-SERVER QUEUE *

by

PETER W. GLYNN

Department of Operations Research Stanford University Stanford, CA 94305, U.S.A.

WARD WHITT

AT & T Bell Laboratories

Room 2C-178

Murray Hill, NJ 07974-0636, U.S.A.

A contribution to the Festschrift in honor of Lajos Takács on his 70th birthday

TECHNICAL REPORT No. 93-1

January 1993

Abstract. We consider the standard single-server queue with unlimited waiting space and the first-in first-out service discipline. We find conditions for the steady-state waiting-time distribution to have small-tail asymptotics of the form $x^{-1} \log P(W > x) \to -\theta^*$ as $x \to \infty$ for $\theta^* > 0$. We require only stationarity of the basic sequence of service times minus interarrival times and a Gärtner-Ellis condition for the cumulant generating function of the associated partial sums, i.e., $n^{-1} \log E e^{\theta S_n} \to \psi(\theta)$ as $n \to \infty$, plus regularity conditions on the decay rate function ψ . The asymptotic decay rate θ^* is the root of the equation $\psi(\theta) = 0$. This result in turn implies a corresponding asymptotic result for the steady-state workload in a queue with general nondecreasing input. This asymptotic result covers the case of multiple independent sources, so that it provides additional theoretical support for a concept of effective bandwidths for admission control in emerging high-speed communication networks.

Keywords. single-server queue, waiting time, workload, tail probabilities, small-tail asymptotics, large deviations, cumulant generating function, counting process, effective bandwidths, admission control, high-speed networks, asynchronous transfer mode.

^{*} The work of the first author was supported by Army Research Office Contract No. DAAL03-91-G-0101 and by the National Science Foundation under Contract No. DDM-9101580.

1. Introduction and Summary

We are pleased to be able to contribute to this Festschrift in honor of Lajos Takács on his 70th birthday. In this paper we try to emulate Takács by seeking the essential mathematics underlying a probability problem of applied relevance. Like Takács (1962, 1963, 1967), we focus on the single-server queue.

In particular, we focus on small-tail asymptotics for the steady-state waiting time W and the steady-state workload L. We find general conditions under which

$$x^{-1}\log P(W>x) \to -\theta^{\circ} \text{ as } x \to \bullet$$
 (1.1)

for $\theta^{\circ} > 0$, and similarly for L. We call the constant θ° in (1.1) the asymptotic decay rate. The following elementary proposition helps put (1.1) in perspective. It is easily proved using integration by parts; e.g., p. 150 of Feller (1971).

Proposition 1. For any random variable Z and positive constant θ^* , the following are equivalent:

(i)
$$x^{-1}\log P(Z>x) \rightarrow -\theta^{\circ} as x \rightarrow \infty$$

(ii)
$$\sup\{\theta \geq 0 : Ee^{\theta Z} < \infty\} = \theta^*;$$

(iii) For all $\varepsilon > 0$, there is an $x_0 = x_0(\varepsilon)$ such that

$$e^{-(\theta^*+\varepsilon)x} \le P(Z > x) \le e^{-(\theta^*-\varepsilon)x}$$
 for all $x > x_0$.

There is currently great interest in small-tail asymptotics such as in (1.1) because of possible applications to the design and control of emerging high-speed communication networks. In particular, it has been recognized that asymptotic decay rate functions (defined below) that determine asymptotic decay rates such as θ^* in (1.1) may be used to create effective bandwidths for admission control and other network resource allocation problems; see Gibbens and Hunt (1991), Kelly (1991), Guerin, Ahmadi and Naghshineh (1991), Chang (1992), Whitt (1992).

Elwalid and Mitra (1992), Baiocchi (1992), Choudhury and Whitt (1992), Sohraby (1992) and Chang, Heidelberger, Juneja and Shahubuddin (1992). The last reference also illustrates how the asymptotic decay rates may be used to speed up simulations. Our approach here is most closely rated to the papers by Whitt (1992), Chang (1992) and Chang et al. (1992). In particular, the results here provide theoretical support for the procedures in Whitt (1992).

In many cases, a stronger limit than (1.1) holds, namely,

$$e^{\theta^*x}P(W > x) \to \alpha^* \text{ as } x \to \infty$$
 (1.2)

for positive constants θ^* and α^* . Then we call α^* the asymptotic constant. It is easy to see that (1.2) implies (1.1) but not conversely. An M/G/I queue for which (1.1) holds but (1.2) does not appears in Example 5 of Abate, Choudhury and Whitt (1992a). Then $P(W > x) \sim \alpha x^{-3/2} e^{-\theta^* x}$ as $x \to \infty$, where $f(x) \sim g(x)$ means that $f(x)/g(x) \to 1$. In this paper we focus on the weaker form (1.1). For work focusing on (1.2), see Abate, Choudhury and Whitt (1992a,b,c), Asmussen (1989), Asmussen and Perry (1992), Neuts (1986), Tijms (1986), van Ommeren (1986) and references in these sources.

When (1.2) holds, a natural approximation for the tail probabilities is $P(W > x) = \alpha^* e^{-\theta^* x}$ for x not too small. Since the asymptotic constant α^* in (1.2) is often not easy to obtain, Abate, Choudhury and Whitt (1992a) suggest the simple approximation $\alpha^* \approx \theta^* EW$. For some purposes, e.g., for percentiles, even $\alpha \approx 1$ is satisfactory. In many cases, $\alpha^* \approx 1$ produces a bound, i.e., $P(W > x) \leq e^{-\theta^* x}$; see p. 269 of Asmussen (1987) and Chang (1992). These exponential approximations can also be used with (1.1), even though (1.1) does not provide as much support as (1.2). However, Example 5 of Abate, Choudhury and Whitt (1992a) shows that the quality of the approximation provided by the asymptotics can deteriorate dramatically when (1.1) holds but (1.2) does not. Moreover, for the admission control problem, it is important to note that the quality of the approximations for the tail probabilities provided by the simple one-term

exponential approximations also can deteriorate dramatically when the number of independent sources increases; see Choudhury, Lucantoni and Whitt (1993).

In this first section, we present our main result and discuss its implications. We give proofs in Sections 2-8 and examples in Section 9. In §1.1 we state our main result for W; in §1.2 we discuss some implications and related results; in §1.3 we state our main results for L, which follow directly from the results for W by discretizing the processes; and in §1.4 we give sufficient conditions for W and L to have the same logarithmic asymptotics. This involves the logarithmic asymptotics of the time-stationary and customer-stationary (embedded-stationary or Palm-stationary) versions of the arrival process. In §1.5 we discuss logarithmic asymptotics for steady-state queue lengths.

1.1 The Main Result

Let $\{X_n : n \ge 1\}$ be a sequence of real-valued random variables and define the associated waiting-time sequence $\{W_n : n \ge 0\}$ recursively by letting $W_0 = 0$ and

$$W_{n+1} = [W_n + X_{n+1}]^+, n \ge 0, \tag{1.3}$$

where $[x]^+ = \max\{x,0\}$. Let $S_0 = 0$ and $S_n = X_1 + ... + X_n$, $n \ge 1$. Let \implies denote convergence in distribution.

Theorem 1. Let $\{X_n : n \ge 1\}$ be strictly stationary. If there exists a function ψ and positive constants θ^* and ϵ^* such that

(i)
$$n^{-1}\log Ee^{\theta S_n} \to \psi(\theta)$$
 as $n \to \infty$ for $|\theta - \theta^*| < \epsilon^*$, (1.4)

(ii) ψ is finite in a neighborhood of θ^* and differentiable at θ^* with $\psi(\theta^*)=0$ and

$$\psi'(\theta^*) > 0, and \tag{1.5}$$

(iii)
$$Ee^{\theta \cdot S_n} < \Leftrightarrow \text{ for } n \ge 1,$$
 (1.6)

then $W_n \Rightarrow W$ as $n \rightarrow \infty$ and (1.1) holds.

A significant feature of Theorem 1 is that there are no independence or Markov assumptions. Instead, we have condition (1.4) involving the asymptotic behavior of the cumulant generating functions of the partial sums S_n , as in the Gärtner (1977)—Ellis (1984) theorem of large deviations theory; see p. 14 of Bucklew (1990). (For a discussion of the connection to cumulants, see Choudhury and Whitt (1992).) Indeed, our proof of Theorem 1 follows large deviations theory, using exponential changes of measure. For additional background on large deviations theory, see Dembo and Zeitouni (1992) and Shwartz and Weiss (1993).

The conditions in Theorem 1 are very general, but they are not necessary, as we show in Example 1 in §9.

A (familiar) key step in proving Theorem 1 is representing W_n as the maximum of reversetime partial sums; i.e.,

$$W_n = S_n - \min_{0 \le k \le n} S_k = \max_{0 \le k \le n} \{S_n - S_k\}, \qquad (1.7)$$

so that, when we extend $\{X_n\}$ to a doubly infinite stationary sequence $\{X_n: -\infty < n < \infty\}$, W_n is distributed as $\tilde{M}_n = \max\{\tilde{S}_k: 0 \le k \le n\}$, where $\tilde{S}_0 = 0$ and $\tilde{S}_k = X_{-1} + \ldots + X_{-k}$. The conditions in Theorem 1 obviously apply to \tilde{S}_k as well as S_k because $Ee^{a\tilde{S}_k} = Ee^{aS_k}$. Since the stationarity is required only for this step, we obtain Theorem 1 immediately from the following result for maxima of partial sums $M_n = \max\{S_k: 0 \le k \le n\}$, which does not require stationarity. We prove the following result in §2.

Theorem 2. Let $\{X_n : n \ge 1\}$ be a sequence of real valued random variables (not necessarily stationary). If there exists a function ψ and positive constants θ^* and ϵ^* such that (1.4)–(1.6) hold and

$$\lim \sup Ee^{\theta X_{\bullet}} < \Rightarrow \text{ for } |\theta| < \epsilon^{\bullet} , \qquad (1.8)$$

then $M_n \to M$ w.p.1 as $n \to \infty$ and

$$x^{-1}\log P(M>x) \to -\theta^* \text{ as } x \to \infty. \tag{1.9}$$

Note that condition (1.8) in Theorem 2 is not needed if $\{X_n\}$ is stationary, because then (1.8) is implied by (1.6) in the case n = 1. For this, recall that $Ee^{\theta_1 Z} < \infty$ when $Ee^{\theta_2 Z} < \infty$ and $\theta_1 < \theta_2$ for any random variable Z by Hölder's inequality; see (21) on p. 47 of Chung (1974).

Also note that condition (1.6) is clearly necessary in Theorem 2, because $M \ge S_n$ for all n. Hence, $Ee^{\theta^*M} = \infty$ if $Ee^{\theta^*S_n} = \infty$ for any n.

We remark that we have also proved a version of Theorem 2 with condition (1.8) replaced by $Ee^{\theta S_n} < \infty$ for $n \ge 1$ for some θ with $\theta > \theta^*$. This alternative condition might be preferred in Theorem 2, but it would require that we strengthen (1.6) in Theorem 1.

In Theorem 1 we have assumed that the basic sequence $\{X_n\}$ is stationary. However, this is not a great restriction because the focus is on the steady-state waiting time W. Given the distribution of W, it is usually possible to choose a stationary version of any given basic sequence $\{X_n\}$ such that $W_n \Rightarrow W$ as $n \to \infty$; e.g., see p. 13 of Borovkov (1976). Of course, the conditions in Theorem 1 apply to this stationary version. However, under regularity conditions, nonstationary versions and stationary versions of the basic sequence will couple so that the conditions for one enable us to verify the conditions for the other.

In other words, W typically does not depend on the initial part of the basic sequence $\{X_n\}$. In contrast, the maximum M in Theorem 2 clearly does depend on the entire sequence $\{X_n\}$. For a simple example, suppose that $\{X_n : n \ge 2\}$ is i.i.d. with a good distribution, but $P(X_1 > x) \sim Ax^{-p}$. Then X_1 influences the tail behavior of S_n for all n and M, but not that of W.

An important role is played by the function ψ in Theorem 1; we call it the (asymptotic) decay rate function. It is significant that ψ is necessarily convex where it is finite, because $\log Ee^{\Phi Z}$ is convex where it is finite for any random variable Z, as can easily be seen by applying Hölder's

inequality. It is important to distinguish the decay rate function ψ from the associated large deviations rate function I(x), defined by

$$I(x) = \sup_{\theta} \{\theta x - \psi(\theta)\}; \qquad (1.10)$$

e.g., see Chapter 1 of Bucklew (1990). The functions ϕ and I are intimately related. Indeed, they are convex conjugates of each other; see p. 183 of Bucklew (1990).

1.2 Implications and Related Results

The conditions of Theorems 1 and 2 are easy to check when the basic sequence $\{X_n\}$ is i.i.d. This special case includes the GI/GI/1 queue (with i.i.d. service times independent of i.i.d. interarrival times), for which it is possible to obtain the stronger result (1.2); e.g., see p. 269 of Asmussen (1987). In this GI/GI/1 case, Abate, Choudhury and Whitt (1992d) have shown that it is also easy to compute the tail probabilities by numerical transform inversion, numerically integrating a contour integral representation for $Ee^{-\ThetaW}$.

Corollary 1. If $\{X_n : n \ge 1\}$ is i.i.d., EX < 0,

$$Ee^{\Phi^*X} = 1 \tag{1.11}$$

and $Ee^{\theta X} < =$ for $-\epsilon < \theta < \theta^* + \epsilon$ for some $\epsilon > 0$, then the conditions of Theorems 1 and 2 hold with $\psi(\theta) = \log Ee^{\theta X}$, so that (1.1) and (1.9) hold.

Proof. Note that $n^{-1}\log Ee^{\theta S_n} = Ee^{\theta X_1} = \psi(\theta)$ when $\{X_n\}$ is i.i.d. Since $\psi(0) = 1$. $\psi'(0) = EX < 0$ and ψ is convex, $\psi'(\theta^*) > 0$.

Thus, for the GI/GI/1 queue, it is easy to see what the decay rate function ψ is. For example, in the M/M/1 queue with service rate 1 and arrival rate ρ , $\psi(\theta) = -\log\{(1-\theta)(1+\theta/\rho)\}$; for the D/M/1 queue, $\psi(\theta) = -\log(1-\theta)-\theta/\rho$; and for the M/D/1 queue. $\psi(\theta) = \theta - \log(1+\theta/\rho)$.

It is worth pointing out that the logarithmic asymptotics in (1.1) tend to be robust. In general, weak convergence of distributions does not imply that large deviations asymptotics converge. However, in this context, weak convergence plus uniform integrability does imply that the cumulant generating function converges, and the logarithmic asymptotics here depends only on the location of the root (and not, for example, the slope at the root). We illustrate by stating a concrete result in the context of Corollary 1.

Corollary 2. Let $\{X_n^{\gamma}: n \geq 1\}$ be i.i.d. for each $\gamma > 0$, where $X_1^{\gamma} \Rightarrow X_1^{\gamma}$ as $\gamma \to 0$ and $Ee^{\Theta X_1^{\gamma}} < M$ for some $\Theta > \Theta_0^{\circ}$ and some M, for all γ . If X_1^{γ} satisfies the conditions of Corollary 1 for each $\gamma \geq 0$, then (1.1) holds for each $\gamma \geq 0$ and $\Theta_{\gamma}^{\circ} \to \Theta_0^{\circ}$ as $\gamma \to 0$.

Proof. Since $X_1^0 \Rightarrow X_1^0 \Rightarrow \gamma \to 0$, $e^{\theta X_1^0} \Rightarrow e^{\theta X_1^0} \Rightarrow \gamma \to 0$. The uniform moment bound implies the uniform integrability needed to obtain $Ee^{\theta X_1^0} \to Ee^{\theta X_1^0}$ as $\gamma \to 0$ for all $\theta < \theta_0^0 + \varepsilon$ for some ε .

In order to understand what the asymptotic decay rate θ^* in (1.1) primarily depends upon, and sometimes to compute θ^* , it is useful to consider heavy-traffic asymptotic expansions for θ^* based on expanding the function $\psi(\theta)$ in a Taylor series expansions about 0. Such heavy-traffic asymptotic expansions are established in Abate, Choudhury and Whitt (1992a), Abate and Whitt (1992) and Choudhury and Whitt (1992). Since $\log Ee^{\theta S_a}$ is the cumulant generating function of S_a , the derivatives of $\psi(\theta)$ are the asymptotic cumulants of S_a . To illustrate, we establish the first term of the heavy-traffic expansion here. The first term coincides with the familiar decay rate associated with exponential heavy-traffic limits; see Kingman (1962), Iglehart and Whitt (1970) and Choudhury and Whitt (1992).

Corollary 3. Consider a family of models indexed by ρ , $0<\rho<1$. Suppose that the assumptions of Theorem 1 hold for each ρ and

(i)
$$EX_{\alpha}(\rho) = -(1-\rho)$$
.

(ii)
$$n^{-1} \operatorname{Var} S_n(\rho) \to \sigma^2 \text{ as } n \to \infty, 0 < \sigma^2 < \infty, \text{ and}$$

(iii)
$$n^{-1}E(S_n(\rho)-(1-\rho)n)^3 \to \gamma \text{ as } n \to \infty, -\infty < \gamma < \infty.$$

Then (1.1) holds with

$$\theta^{\bullet}(\rho) = \frac{2(1-\rho)}{\sigma^2} + o(1-\rho) \text{ as } \rho \to 1.$$

Proof. Since $\log Ee^{\theta S_n}$ is the cumulant generating function of S_n , we can apply Taylor's theorem to obtain

$$n^{-1}\log Ee^{\theta S_n} = -\theta(1-\rho) + \frac{\theta^2 \operatorname{Var}(S_n)}{2n} + o(\theta^2) \text{ as } \theta \to 0$$

uniformly in ρ and η , using condition (iii) to get the uniformity in n; e.g., see (4') on p. 268 of Chung (1974). Hence

$$\psi(\theta) = -\theta(1-\rho) + \frac{\theta^2 \sigma^2}{2} + o(\theta^2) \text{ as } \theta \to 0$$

uniformly in ρ , so that the desired conclusion follows.

Another easy case is when the partial sums S_n are Gaussian (but possibly dependent) for all n. When S_n is Gaussian, Theorem 1 takes a very simple form. In particular, then (1.1) holds with θ^* in Corollary 3. The Gaussian assumption holds approximately in an $E_k/E_m/1$ queue for suitably large k and m. (As usual, E_k stands for Erlang of order k.) A direct Gaussian approximation has also been proposed and studied by Addie and Zuckerman (1993). This analysis provides additional justification for the heavy-traffic approximation, because it does not (at least directly) require a high traffic intensity.

Corollary 4. Suppose that S_n is Gaussian with negative mean m_n and finite variance σ_n^2 for all $n \ge 1$. If $m_n/n \to m$ and $\sigma_n^2/n \to \sigma^2$ as $n \to \infty$, where $m < 0 < \sigma^2$, then the conditions of Theorem 2 hold with $\psi(\theta) = \theta m + \theta^2 \sigma^2/2$, so that (1.9) holds with $\theta^* = -2m/\sigma^2 > 0$. If, in addition, the basic sequence $\{X_n\}$ is stationary, then the conditions of Theorem 1 hold, so that

(1.1) holds.

Proof. Recall that $E\exp(\theta S_n) = \exp(\theta m_n + \theta^2 \sigma^2/2)$ when S_n is Gaussian with mean m_n and variance σ_n^2 .

In queueing theory, (1.3) is the familiar Lindley equation associated with a single-server queue with unlimited waiting room and the first-in first-out service discipline. Then $X_n = V_n - U_n$ where, for $n \ge 1$, V_n is the service time of customer n and U_n is the interarrival time between customers n and n+1. With this indexing, we begin with a first customer arriving at an empty system.

Another queueing model that leads to the representation $X_n = V_n - U_n$ is the queue length in a discrete-time single-server queue. Then we interpret V_n as the number of arrivals at epoch n and U_n as the number of potential departures at epoch n. For this representation to be valid, we usually require special Markov or deterministic assumptions in the service process, or "autonomous service;" see p. 235 of Borovkov (1976). We use this below in §1.3. For the ATM networks it is often reasonable to assume deterministic service, so that this Lindley equation representation is indeed appropriate. For example, if there is at most one service completion at each epoch, then $U_n = 1$ for all n. This model variant is considered by Chang (1992), Sohraby (1992) and Chang et al. (1992). These authors also focus on the Gärtner-Ellis condition in (1.4), but Theorem 1 here seems to be new.

Given Theorems 1 and 2, we want to know when the conditions are satisfied. In the queueing context, the conditions can be expressed in terms of the two sequences $\{U_n : n \ge 1\}$ and $\{V_n : n \ge 1\}$ separately when the sequences $\{U_n\}$ and $\{V_n\}$ are independent. (However, note that such independence is not required in Theorem 1.)

To state the result, let $S_n^* = V_1 + ... + V_n$ and let $S_n^* = U_1 + ... + U_n$.

Proposition 2. Suppose that $X_n = V_n - U_n$, where $\{V_n : n \ge 1\}$ and $\{U_n : n \ge 1\}$ are

independent sequences of nonnegative random variables. If there exist functions ψ_v and ψ_u and positive constants θ^{\bullet} , ε^{\bullet} and M such that

(i)
$$n^{-1} \log Ee^{\theta S_a^*} \to \psi_{\nu}(\theta) \text{ as } n \to \infty \text{ for } |\theta - \theta^*| < \varepsilon^*$$
, (1.12)

(ii)
$$\psi_{\nu}$$
 is finite in a neighborhood of θ^{\bullet} and differentiable at θ^{\bullet} , (1.13)

(iii)
$$Ee^{\theta^*S_n^*} < \infty \text{ for } n \ge 1,$$
 (1.14)

(iv)
$$Ee^{\theta V_n} < M$$
 for $n \ge 1$ and all $|\theta| < \varepsilon^{\bullet}$, (1.15)

$$(v) n^{-1} \log E e^{-\theta S_n^{\alpha}} \to \Psi_n(-\theta) \text{ as } n \to \infty, \text{ for } |\theta - \theta^{\circ}| < \varepsilon^{\circ}, \qquad (1.16)$$

(vi)
$$\psi_n$$
 is finite in a neighborhood of $-\theta^*$ and differentiable at $-\theta^*$, (1.17)

(vii)
$$Ee^{-\theta U_n} < M$$
 for $n \ge 1$ and all $|\theta| < \epsilon^{\bullet}$ and (1.18)

$$(viii) \psi(\theta^*) = 0 \text{ and } \psi'(\theta^*) > 0 \text{ for } \psi(\theta) = \psi_v(\theta) + \psi_u(-\theta) , \qquad (1.19)$$

then $\{X_n\}$ satisfies conditions (1.4)-(1.6) and (1.8) with decay rate function ψ , so that (1.9) holds. If, in addition, $\{(U_n, V_n)\}$ is stationary, then $\{X_n\}$ is stationary and (1.1) holds. Proof. By the independence,

$$Ee^{4S_a} = Ee^{4(S_a^* - S_a^*)} = Ee^{4S_a^*} Ee^{-4S_a^*}$$

so that

$$\log Ee^{aS_a} = \log Ee^{aS_a^*} + \log Ee^{-aS_a^*}$$

Since $S_n^u \ge 0$, $Ee^{-0.5^u} \le 1$. Similarly, $Ee^{0.5^u} = Ee^{0.5^u} \cdot Ee^{-0.5^u}$. Hence, it is clear that the assumed conditions here imply the conditions in Theorem 1.

Assuming that the arrival and service processes are independent, we can treat them separately. To obtain further results for these separate processes, it is useful to have a relation between the asymptotics for a counting process and the asymptotics for its inverse partial sum process. For this purpose, we apply a result from Glynn and Whitt (1993).

Let $\{T_n : n \ge 0\}$ be a nondecreasing sequence of random variables with $T_0 = 0$. We think

of T_n as the arrival epoch of customer n in the queue; then $T_n = U_1 + ... + U_n$. let $\{N(t): t \ge 0\}$ be the associated counting process defined by

$$N(t) = \max\{n \ge 0 : T_n \le t\}, t \ge 0.$$
 (1.20)

The (familiar) key relation between T_n and N(t) that we exploit is

$$\{N(t) \ge n\} = \{T_n \le t\} \tag{1.21}$$

for all nonnegative n and t.

A process $\{Z(t): t \ge 0\}$ will be said to satisfy the Gartner-Ellis condition with decay rate function ψ if

$$\lim_{t \to \infty} t^{-1} \log E e^{\theta Z(t)} = \psi(\theta) \text{ for all } \theta \in \mathbb{R} . \tag{1.22}$$

For a discrete-time process, we let t run through the positive integers in (1.22).

The associated decay rate function ψ will be said to satisfy the auxiliary large deviations (LD) regularity conditions if (1.23)–(1.26) below hold:

$$\beta = \inf\{\theta : \psi(\theta) = +\infty\} > 0, \tag{1.23}$$

$$\psi$$
 is differentiable everywhere in $(-\infty, \beta)$, (1.24)

$$\lim_{\theta \uparrow \delta} \psi'(\theta) = + \infty, \text{ and}$$
 (1.25)

$$\lim_{\theta \uparrow \theta} \psi(\theta) = \psi(\beta) \ . \tag{1.26}$$

The conditions (1.22)–(1.26) are standard in the large deviations literature. In particular, under conditions (1.22)–(1.26), the process $\{Z(t): t \ge 0\}$ satisfies the Gärtner (1977) – Ellis (1984) theorem, i.e., the large deviations principle holds for $\{Z(t): t \ge 0\}$ with rate function I in (1.10); see pp. 42-50 of Dembo and Zeitouni (1992).

The following result is proved in Glynn and Whitt (1993). let ψ^{-1} be the inverse function of ψ . Note that ψ is nondecreasing, and strictly increasing where it is finite. Hence, for x and y finite, $\psi^{-1}(y) = x$ if and only if $\psi(x) = y$.

Theorem 3. If the counting process $\{N(t): t \ge 0\}$ satisfies (1.22)–(1.26), then the inverse partial sum process $\{T_n: n \ge 0\}$ does too, with the possible exception of (1.22) for $\theta = \beta_T$. Similarly, if $\{T_n: n \ge 0\}$ satisfies (1.22)–(1.26), then $\{N(t): t \ge 0\}$ does too, with the possible exception of (1.22) for $\theta = \beta_N$. In particular, then (1.22) holds for both processes, i.e.,

$$\lim_{t \to \infty} t^{-1} \log E e^{\theta N(t)} = \psi_N(\theta) \tag{1.27}$$

and

$$\lim_{n\to\infty} n^{-1}\log Ee^{\theta T_n} = \psi_T(\theta) \tag{1.28}$$

both hold (with the noted exceptions) and

$$\psi_N(\theta) = -\psi_T^{-1}(-\theta) , \qquad (1.29)$$

where they are finite.

Thus, subject to regularity conditions, given the Gärtner-Ellis asymptotics for one of N or T, we obtain the Gärtner-Ellis asymptotics for the other directly and have the inverse relation (1.29). This parallels previous relations between other limits for N and T; e.g., see Iglehart and Whitt (1971), §7 of Whitt (1980), Theorems 3 and 6 of Glynn and Whitt (1988a) and Theorem 1 of Glynn and Whitt (1988b).

For example, we can apply Theorem 3 to obtain the Gärtner-Ellis limit (1.28) for the partial sums S_n^u from the Gärtner-Ellis limit (1.27) for the counting process N(t) derived for batch Markovian arrival processes in Theorem 1 of Choudhury and Whitt (1992). Abate, Choudhury and Whitt (1992c) obtain (1.2) for BMAP/GI/1 queues, while the results here yield (1.1) for BMAP/G/1 queues, without requiring that the service times be i.i.d. Sufficient conditions for

(1.22) in terms of embedded regenerative structure are also given in Theorem 7 of Glynn and Whitt (1993).

We now show that deterministic sequences provide upper bounds on θ^* when $\{U_n\}$ and $\{V_n\}$ are independent sequences; see §8 of Abate, Choudhury and Whitt (1993a) for related results. We use the queueing notation G/G/1 to refer to a general stationary sequence $\{(U_n, V_n)\}$ of interarrival times and service times.

Proposition 3. Among G/G/I models satisfying the assumptions of Proposition 2, the asymptotic decay rate θ^{\bullet} is maximized (a) by deterministic service times among all stationary service-time sequences $\{V_n\}$ with given mean EV_n , and (b) by deterministic interarrival times among all stationary interarrival-times sequences $\{U_n\}$ with given mean EU_n .

Proof. By Jensen's inequality, $Ee^{\theta Z} \ge e^{\theta EZ}$ for any random variable Z, so that $\log Ee^{\theta S_u^2} \ge \log e^{\theta ES_u^2} = n\theta EV_1$ and $\log Ee^{-\theta S_u^2} \ge \log e^{\theta ES_u^2} = n\theta EU_1$. Hence, if ψ_v^D and and ψ_u^D denote the decay rate functions in the deterministic cases, then $\psi_v(\theta) \ge \psi_v^D(\theta)$ and $\psi_u(-\theta) \ge \psi_u^D(-\theta)$ for all $\theta > 0$, so that the roots in (1.19) must be ordered as indicated.

More generally, we can establish stochastic comparisons between any two G/G/1 systems. Proposition 4. Consider two G/G/1 queues satisfying the assumptions of Theorem 1. If $Ee^{\theta S_1^1} \leq Ee^{\theta S_1^1}$ for all $\theta \geq 0$ and all n suitably large, then $\theta_2^* \leq \theta_1^*$.

Proof. The condition implies that $\psi_1(\theta) \le \psi_2(\theta)$ for all $\theta \ge 0$. Hence, the roots θ_i^* of $\psi_i(\theta) = 0$ must be ordered by $\theta_2^* \le \theta_1^*$.

As in Whitt (1992), when $\{U_n\}$ and $\{V_n\}$ are independent, we can characterize the arrival and service decay rate functions $\psi_n(-\theta)$ and $\psi_n(\theta)$ from the asymptotic decay rates θ^* observed in G/D/1 and D/G/1 queues. To do this, we must consider all possible arrival rates ρ . $0 < \rho < 1$, so that the asymptotic decay rate θ^* becomes a function $\theta^*(\rho)$, $0 < \rho < 1$. Let $\psi_n(-\theta)$ refer to the case in which $EU_n = 1$ and let the case of arrival rate ρ be obtained by

considering interarrival times U_n/ρ for all n, i.e., simple time scaling.

Proposition 5. For G/G/I models satisfying the assumptions of Proposition 2, (a) the arrival asymptotic decay rate function $\psi_u(-\theta)$ with arrival rate 1 is determined by the decay rate $\theta^*(\rho)$ in G/D/I models with arrival rate ρ , $0 < \rho < 1$, i.e., by the equation

$$\psi_{\mu}(-\theta^{*}(\rho)/\rho) + \theta^{*}(\rho) = 0, 0 < \rho < 1.$$
 (1.30)

(b) The service asymptotic decay rate function $\psi_{\nu}(\theta)$ with service rate 1 is determined by the decay rate $\theta^{\bullet}(\rho)$ in D/G/1 models with arrival rate ρ , $0 < \rho < 1$, i.e., by the equation

$$\psi_{\nu}(\theta^{\bullet}(\rho)) - \theta^{\bullet}(\rho)/\rho = 0. \qquad (1.31)$$

Proof. Note that $\psi_n(-\theta)$ is a decreasing convex function with $\psi'_n(0) = -1$. Hence, the values of $\psi_n(-\theta)$ for $\theta > 0$ are determined by the intersection with all lines through the origin with slopes less than -1. This is provided by (1.30), after making the change of variables $\theta(\rho) = \theta^*(\rho)/\rho$. Similarly, $\psi_n(\theta)$ is an increasing convex function with $\psi'_n(0) = 1$. Hence, the values of $\psi_n(\theta)$ for $\theta > 0$ are determined by the intersection with all lines through the origin with slope greater than +1. This is determined by (1.31).

1.3 A Continuous-Time Analog: The Workload

We can apply Theorems 1 and 2 to obtain corresponding results for continuous-time workload processes; we will only discuss the analog of Theorem 1. Paralleling (1.7), suppose that we have a continuous-time workload process $\{L(t): t \ge 0\}$ defined in terms of a continuous-time net input process $\{Y(t): t \ge 0\}$ by applying the usual reflection map, i.e.,

$$L(t) = Y(t) - \inf\{Y(s) : 0 \le s \le t\}, \ t \ge 0, \tag{1.32}$$

with L(0) = 0. Moreover, let the net input process be defined in terms of a total input process $\{I(t): t \ge 0\}$ with nondecreasing sample paths by

$$Y(t) = I(t) - t, t \ge 0. (1.33)$$

In the G/G/1 queue, I(t) represents the total work in service time to arrive in the interval [0,t], i.e., the sum of all service times of all arrivals in [0,t], but here I(t) can be more general. For example, this formulation includes fluid models such as the Markov modulated fluid models in Elwalid and Mitra (1992) as a special case (without directly requiring the Markov assumption).

Paralleling Theorem 1, we will work with a version of I(t) that has stationary increments. We prove the following result in §4.

Theorem 4. Let the net input process $\{Y(t):t\geq 0\}$ have stationary increments with $EY(t)=(\rho-1)t$ where $\rho<1$. If there exists a function ψ and positive constants θ^* and ε^* such that the analogs of (1.4) and (1.6) hold, i.e., if

$$t^{-1}\log Ee^{\theta Y(t)} \to \psi(\theta) \text{ as } t \to \infty \text{ for } |\theta - \theta^*| < \epsilon^*$$
 (1.34)

and

$$Ee^{0.Y(t)} < \Rightarrow \text{ for all } t > 0, \tag{1.35}$$

and if (1.5) holds for this ψ , then $L(t) \Rightarrow L$ as to $t \rightarrow \Rightarrow$ and

$$x^{-1}\log P(L>x) \to -\theta^* \text{ as } x \to -\infty. \tag{1.36}$$

Theorem 4 easily applies to superpositions of independent processes, as we now show. Proposition 6. Consider the workload process L(t) in (1.32) and (1.33) with $I(t) = I_1(t) + ... + I_n(t)$, where $I_1(t), ..., I_n(t)$ are mutually independent nondecreasing processes each with stationary increments satisfying

$$t^{-1}\log Ee^{\theta I_i(t)} \rightarrow \Psi_i(\theta) \text{ for } |\theta-\theta^*| < \varepsilon^*$$
.

and

$$Ee^{\theta^* l_i(t)} < - \text{for all } t > 0 \text{ and } i$$
.

If (1.5) holds for

$$\psi(\theta) = \psi_1(\theta) + ... + \psi_n(\theta) - \theta,$$

then the conditions of Theorem 4 hold, so that (1.36) holds.

Proof. By the independence,

$$\log Ee^{\theta Y(t)} = \log Ee^{\theta I_1(t)} + ... + \log Ee^{\theta I_n(t)} - \theta t . \quad \blacksquare$$

The following proposition treats the standard case in queueing, in which the total input I(t) is the sum of all the service times of all arrivals in the interval [0,t]. We prove the following in §7.

Proposition 7. Consider a total input process defined by

$$I(t) = \sum_{i=1}^{A(t)} V_i, \ t \ge 0, \tag{1.37}$$

Suppose that $\{V_n\}$ is independent of $\{A(t)\}$,

$$n^{-1}Ee^{\frac{\hat{\theta}}{1-1}} \xrightarrow{\psi_{\nu}(\theta)} as \ n \xrightarrow{} = for \ all \ \theta \ in \ a \ neighborhood \ of \ \hat{\theta}$$

and

$$t^{-1}\log Ee^{\theta A(t)} \to \psi_A(\theta)$$
 as $t \to \infty$ for all θ in a neighborhood of $\psi(\hat{\theta})$

where ψ_A is continuous at $\psi_*(\hat{\theta})$. Then

$$t^{-1} E e^{\hat{\theta} I(t)} \rightarrow \Psi_A(\Psi_{\pi}(\hat{\theta}))$$
 as $t \rightarrow \infty$.

1.4 Palm Equivalence for the Gärtner-Ellis Limits: Relating W and L:

The asymptotics for W and L differ, in part, because W is based on the customer-stationary (embedded-stationary or Palm-stationary) sequence $\{U_n\}$ while L is based on the counting process $\{A(t)\}$ with stationary increments, which is associated with the time-stationary sequence, say $\{U_n^*\}$, connected by the Palm transformation, e.g., see Franken et al. (1981). However, we

anticipate that we should have $\theta_W^* = \theta_L^*$. To establish that relation, we would like to have Palm equivalence for the Gartner-Ellis limits, i.e., we would like to be able to say that $n^{-1}\log Ee^{\theta S_n^*} \to \psi_u(\theta)$ as $n \to \infty$ if and only if $n^{-1}\log Ee^{\theta S_n^*} \to \psi_u^*(\theta)$ as $n \to \infty$ and $\psi_u = \psi_u^*$, where $S_n^{u^*} = U_1^* + ... + U_n^*$, $n \ge 1$. We establish a weaker result here. We show that if both limits hold with the limit functions ψ_u and ψ_u^* satisfying regularity conditions, then $\psi_u = \psi_u^*$. We then use this property to provide conditions under which $\theta_L^* = \theta_W^*$.

We start by relating the asymptotics for L and W when the service times are i.i.d. As in Theorem 2 and §2 of Abate, Choudhury and Whitt (1992b), we apply the generalized Takacs (1963) relation between W and L in a G/GI/1 queue (with i.i.d. service times that are independent of the arrival process); see (1.38) below and (4.5.9) on p. 129 of Franken et al. (1981).

Proposition 8. In a G/GI/1 queue, (1.1) holds if and only if (1.36) holds and $\theta_W^* = \theta_L^*$.

Proof. The generalized Takacs relation yields

$$Ee^{\theta L} = 1 - \rho + \rho Ee^{\theta W} Ee^{\theta V_e}, \qquad (1.38)$$

where V_e has the stationary-excess or equilibrium-residual-life distribution associated with the service-time distribution. By Proposition 3 here, Theorem 10 of Abate, Choudhury and Whitt (1992a) and Lemma 1 of Abate, Choudhury and Whitt (1992b), $Ee^{\Phi V_1} < \infty$ if $Ee^{\Phi W} < \infty$.

We now apply Proposition 8 to obtain a form of Palm equivalence for the Gärtner-Ellis limits.

We prove the following result in §5.

Theorem 5. Let A(t) be a counting process associated with a non-deterministic time-stationary sequence $\{U_n^*\}$ and let S_n^* be the partial sums associated with the corresponding customer-stationary sequence $\{U_n^*\}$. Assume that the decay-rate function associated with A, ψ_A , satisfies the auxiliary LD regularity conditions (1.23)–(1.26) with limit of support β_A in (1.23). Assume that

$$Ee^{\theta A(t)} < \infty \text{ for all } t > 0 \text{ and } \theta < \beta_A$$
 (1.39)

and

$$t^{-1}\log Ee^{\theta A(t)} \to \psi_A(\theta) \text{ as } t \to \infty \text{ for } \theta < \beta_A$$
. (1.40)

Assume that

$$n^{-1}\log Ee^{-\theta S_n^n} \to \psi_n(-\theta) \text{ as } n \to \infty \text{ for all } \theta > 0$$
, (1.41)

where $\psi_{u}(-\theta)$ is finite and differentiable for all $\theta > 0$. Then

$$\psi_{\mu}(-\theta) = \psi_{\mu}^{\bullet}(-\theta) = -\psi_{A}^{-1}(\theta) \text{ for all } \theta > 0.$$
 (1.42)

We now relate the logarithmic asymptotics for W and L in a general G/G/1 queue when the arrival and service processes are independent (but the service times need not be i.i.d.). We prove the following result in §6.

Theorem 6. Consider a G/G/I queue in which the service times $\{V_n\}$ are stationary and independent of the arrival process. Let the arrival process satisfy the assumptions of Theorem 5. Let the service decay rate function ψ_n satisfy the auxiliary LD regularity conditions (1.23)–(1.26) with limit of support β_n in (1.23). Assume that

$$Ee^{\theta S_n^*} < \infty \text{ for all } n \ge 1 \text{ and } \theta < \beta_n$$
 (1.43)

and

$$n^{-1}\log Ee^{\theta S_n^2} \to \psi_{\nu}(\theta) \text{ as } n \to \infty \text{ for } \theta < \beta_{\nu} .$$
 (1.44)

Then (1.1) and (1.36) both hold with $\theta_W^*(\rho) = \theta_L^*(\rho)$ for each ρ , $0 < \rho < 1$.

1.5 Queue Lengths

In this section we discuss the logarithmic asymptotics for the steady-state queue length (number in system). Let Q and Q^a be the steady-state queue length at an arbitrary time and at an arrival epoch, respectively, which we assume are well defined. As in §1.3, let G/GI/I mean i.i.d

service times that are independent of general stationary interarrival times. We prove the following in §8.

Proposition 9. In the G/Gl/1 queue, (1.1) holds if and only if the the analogs of (1.1) hold for Q and Q^a , in which case

$$\theta_Q^* = Q_{Q^*}^* = \log E e^{\theta_W^* V_1} = \psi_v(\theta_W^*)$$
 (1.45)

2. Proof of Theorem 2

In this section we prove Theorem 2. For this purpose, we perform a change of measure for each n. In particular, for each $n \ge 1$, let P_n^* be the probability measure on \mathbb{R}^n defined by

$$P_n^*(dx_1, \dots, dx_n) = \frac{\exp(\theta^* S_n)}{E\exp(\theta^* S_n)} P(X_1 \in dx_1, \dots, X_n \in dx_n)$$
$$= \exp(\theta^* S_n - \psi_n(\theta^*)) P(X_1 \in dx_1, \dots, X_n \in dx_n) , \qquad (2.1)$$

where $\psi_n(\theta) = \log E \exp(\theta S_n)$ and $\psi_n(\theta^*) < \infty$ for $n \ge 1$ by (1.6).

We base our proof on the following strengthened form of the weak law of large numbers. This is closely related to claim 1 on p. 17 of Bucklew (1990) in his proof of the Gärtner-Ellis theorem. However, we only make assumptions locally around θ^* , whereas Bucklew's assumptions are more global. We will need the cases k=0 and k=1 in our proof of Theorem 2. We prove Theorem 7 in §3.

Theorem 7. Let k be a fixed nonnegative integer. Under the conditions of Theorem 2 (excluding (1.8) if k = 0), for each $\epsilon > 0$ there exists n_0 and $\eta = \eta(\epsilon) \in [0,1)$ such that

$$P_n^* \left[\left| \frac{S_{n-k}}{n} - v \right| > \epsilon \right] \le \eta^n \text{ for } n \ge n_0 \ . \tag{2.2}$$

Since M_n is nondecreasing, $M_n \to M$ w.p.1. The desired result (1.9) implies that M must be proper. Since $P(M > x) = P(T(x) < \infty)$, where

$$T(x) = \inf\{n \ge 0 : S_n > x\},$$
 (2.3)

it suffices to show that

$$x^{-1} \log P(T(x) < \infty) \rightarrow -\theta^* \text{ as } x \rightarrow \infty$$
 (2.4)

Let $\lfloor x \rfloor$ be the greatest integer less than or equal to x and let $\lceil x \rceil$ be the least integer greater than or equal to x. Now, for ε and v given, and any x and $n(\varepsilon)$,

$$P(T(x) < \infty) = \sum_{j=1}^{\infty} P(T(x) = j)$$

$$\leq \sum_{j=1}^{n(\varepsilon)} P(T(x) = j) + \sum_{j=n(\varepsilon)+1}^{\lfloor x(1-\varepsilon) \wedge j \rfloor} P(T(x) = j)$$

$$+ \sum_{j=\lceil x(1-\varepsilon) \wedge j \rceil} P(T(x) = j) + \sum_{j=\lceil x(1+\varepsilon) \wedge j \rceil}^{\infty} P(T(x) = j) . \quad (2.5)$$

Given ε , we choose $n(\varepsilon)$ in (2.5) so that for all $n \ge n(\varepsilon)$ we simultaneously have

$$|n^{-1}\psi_n(\theta^*)| < \min\{-\frac{\log \eta}{2}, \epsilon\}$$
 (2.6)

and

$$P_n^* \left(\left| n^{-1} S_{n-k} - \nu \right| > \frac{\varepsilon \nu}{1+\varepsilon} \right) \le \eta^n \tag{2.7}$$

for k = 0 and 1 for some η with $0 \le \eta < 1$. This is possible because of assumption (1.4) and Theorem 7.

For the first term in (2.5),

$$P(T(x) = j) \le P(S_j > x)$$

$$\le E_j^* \{ \exp(-\theta^* S_j + \psi_j(\theta^*)) ; S_j > x \}$$

$$\le \exp(-\theta^* x) E_j^* \{ \exp(\psi_j(\theta^*)) ; S_j > x \}$$

$$\le \exp(-\theta^* x) \exp(\psi_j(\theta^*)) .$$
(2.8)

We use (1.6) to ensure that (2.8) is finite.

For the second term in (2.5), note that (starting with the reasoning in (2.8))

$$P(T(x) = j) \le \exp(-\theta^* x) E_j^* [\exp(\psi_j(\theta^*)); S_j > x],$$

where

$$E_{j}^{*}[\exp(\phi_{j}(\theta^{*}); S_{j} > x] \leq \exp\left[j\left(\frac{-\log\eta}{2}\right)\right] P_{j}^{*}(S_{j} > x)$$

$$\leq \exp\left[j\frac{(-\log\eta)}{2}\right] P_{j}^{*}\left[S_{j} > \frac{v_{j}}{1-\varepsilon}\right]$$

$$\leq \exp\left[j\frac{(-\log\eta)}{2}\right] P_{j}^{*}\left[(j^{-1}S_{j} - v) > \frac{v}{1-\varepsilon} - v\right]$$

$$\leq \exp\left[j\frac{(-\log\eta)}{2}\right] P_{j}^{*}\left[|j^{-1}S_{j} - v| > \frac{\varepsilon v}{1+\varepsilon}\right]$$

$$\leq \exp\left[j\left(\frac{-\log\eta}{2}\right)\right] \eta^{j} \leq \exp\left[j\frac{\log\eta}{2}\right]. \tag{2.9}$$

Hence,

$$\sum_{j=n(\epsilon)+1}^{\lceil x(1-\epsilon)\sqrt{\gamma}\rceil} P(T(x) = j) \le \exp(-\theta^* x) \sum_{j=1}^{\infty} \eta^{j/2} \le \exp(-\theta^* x) (1-\sqrt{\eta})^{-1} . \tag{2.10}$$

For the third term in (2.5),

$$P(T(x) = j) \le \exp(-\theta^* x) E_j^* \left[\exp \psi_j(\theta^*) ; S_j > x\right], \qquad (2.11)$$

where

$$E_j^*\{\exp(\psi_j(\theta^*))\colon S_j>x\}\le \exp(\psi_j(\psi^*))\le \exp(j\varepsilon)\le \exp(\varepsilon x(1+\varepsilon)/v)\ . \tag{2.12}$$

For the fourth term in (2.5),

$$P(T(x) = j) \le P(S_{j-1} \le x, S_j > x)$$

$$\le E_j^* [\exp(-\theta^* S_j + \psi_j(\theta^*); S_{j-1} \le x, S_j > x]$$

$$\le \exp(-\theta^* x) \exp(\psi_j(\theta^*) P_j^* (S_{j-1} \le x),$$

where

$$P_{j}^{*}(S_{j-1} \leq x) \leq P_{j} \left[S_{j-1} \leq \frac{v_{j}}{1+\varepsilon} \right] = P_{j}^{*} \left[\frac{S_{j-1}}{j} \leq \frac{v}{1+\varepsilon} \right]$$

$$\leq P_{j}^{*} \left[\left| \frac{S_{j-1}}{j} - v \right| > \frac{\varepsilon v}{1+\varepsilon} \right] \leq \eta^{j}$$

by Theorem 5 with k = 1. Since $\psi_j(\theta^*) \le -(\log \eta)/2$ by (2.6) for j in this sum,

$$\sum_{j=\lfloor x(1+\epsilon) \wedge j}^{\infty} P(T(x) = j) \le \exp(-\theta^* x) \sum_{j=0}^{\infty} \eta^{j/2} \le \exp(-\theta^* x) (1 - \sqrt{\eta})^{-1}. \tag{2.13}$$

Combining (2.5), (2.8), (2.10), (2.12) and (2.13), we obtain

$$P(T(x) < \infty) \le \exp(-\theta^* x) \left\{ \sum_{j=1}^{n(\epsilon)} \exp(\psi_j(\theta^*)) + (1 - \sqrt{\eta})^{-1} + \left[\frac{2\epsilon x}{v} + 1 \right] \exp(\epsilon x (1 + \epsilon) N) + (1 - \sqrt{\eta})^{-1} \right\}.$$

Hence, using condition (1.6),

$$\overline{\lim}_{x\to\infty} x^{-1} \log P(T(x) < \infty) \le -\theta^* + \varepsilon (1+\varepsilon) \wedge .$$

Since & was arbitrary,

$$\lim_{x \to \infty} x^{-1} \log P(T(x) < \infty) \le -\theta^* . \tag{2.14}$$

We now establish the lower bound. For this purpose, let $m(\epsilon) = \lceil x(1+\epsilon)/\nu \rceil$. Then

$$P(T(x) < \infty) \ge P(S_{m(\varepsilon)} > x)$$

$$\ge E_{m(\varepsilon)}^* \left[\exp(-\theta^* S_{m(\varepsilon)} + \psi_{m(\varepsilon)}(\theta^*) ; S_{m(\varepsilon)} > x \right]$$

$$\ge E_{m(\varepsilon)}^* \left[\exp(-\theta^* S_{m(\varepsilon)} + \psi_{m(\varepsilon)}(\theta^*) ; S_{m(\varepsilon)} > \frac{m(\varepsilon) \nu}{1+\varepsilon} \right]$$

$$\ge E_{m(\varepsilon)}^* \left[\exp(-\theta^* S_{m(\varepsilon)} + \psi_{m(\varepsilon)}(\theta^*) ; m(\varepsilon)^{-1} | S_{m(\varepsilon)} - \nu | < \frac{\varepsilon \nu}{1+\varepsilon} \right]$$

$$\ge E_{m(\varepsilon)}^* \left[\exp(-\theta^* \nu \frac{(1+2\varepsilon)}{1+\varepsilon} m(\varepsilon)) + \psi_{m(\varepsilon)}(\theta^*) ; | m(\varepsilon)^{-1} S_{m(\varepsilon)} - \nu | < \frac{\varepsilon \nu}{1+\varepsilon} \right]$$

$$\ge \exp \left[-\theta^* \nu \frac{(1+2\varepsilon)}{1+\varepsilon} m(\varepsilon) + \psi_{m(\varepsilon)}(\theta^*) \right] P_{m(\varepsilon)}^* \left[| m(\varepsilon)^{-1} S_{m(\varepsilon)} - \nu | < \frac{\varepsilon \nu}{1+\varepsilon} \right].$$

Since

$$P_{m(\varepsilon)}^{\bullet}\left[\left|m(\varepsilon)^{-1}S_{m(\varepsilon)}-\nu\right|<\frac{\varepsilon\nu}{1+\varepsilon}\right]\to 1 \text{ as } x\to\infty$$

by Theorem 5,

$$\underline{\lim}_{x \to \infty} x^{-1} \log P(T(x) < \infty) \ge \underline{\lim}_{x \to \infty} \left\{ -\theta^* v \frac{(1+2\varepsilon)}{1+\varepsilon} \frac{m(\varepsilon)}{x} - \frac{\varepsilon r \eta(\varepsilon)}{x} \right\}$$

$$\ge -\theta^* (1+2\varepsilon) - \varepsilon (1+\varepsilon) / v.$$

Since ε was arbitrary, we conclude that

$$\lim_{x \to \infty} x^{-1} \log P(T(x) < \infty) \ge -\theta^{\circ} . \tag{2.15}$$

Combining (2.14) and (2.15) completes the proof.

3. Proof of Theorem 7

As before, let $\psi_n(\theta) = \log E e^{\theta S_n}$ and recall that $n^{-1}\psi_n(\theta) \to \psi(\theta)$ as $n \to \infty$ for $|\theta - \theta^*| < \epsilon^*$ where θ^* and ϵ^* are as assumed. We start with the case k = 0. Then, for each $\theta = 0$.

$$P_n^{\bullet}(n^{-1}S_n > v + \varepsilon) \le \exp(-\theta n(v + \varepsilon))E_n^{\bullet}\exp(\theta S_n)$$
,

where

$$\exp(-\theta n(\mathbf{v}+\varepsilon))E_n^*\exp(\theta S_n) = \exp(-\theta n(\mathbf{v}+\varepsilon))\int \exp(\theta x)\exp(\theta^*x-\psi_n(\theta^*))P(S_n \in dx)$$
$$= \exp(-\theta n(\mathbf{v}+\varepsilon))\exp(\psi_n(\theta+\theta^*)-\psi_n(\theta^*)).$$

We choose n_0 in Theorem 7 suitably large so that $\psi_n(\theta + \theta^*) < \infty$, which is possible by (1.4) and (1.5). We use the fact that $Ee^{\theta_1 Z} < \infty$ when $Ee^{\theta_2 Z} < \infty$ and $0 < \theta_1 < \theta_2$, hence

$$\overline{\lim}_{n \to \infty} n^{-1} \log P_n^*(n^{-1}S_n > v + \varepsilon) \le \psi(\theta^* + \theta) - \psi(\theta^*) - \theta(v + \varepsilon) . \tag{3.1}$$

However, by Taylor's theorem,

$$\psi(\theta + \theta^*) - \psi(\theta^*) - \theta(v + \varepsilon) = \psi'(\theta^*)\theta + o(\theta) - \theta(v + \varepsilon) \text{ as } \theta \to 0$$
$$= -\theta\varepsilon + o(\theta) \text{ as } \theta \to 0.$$

Hence, we can choose θ_1 with $0 < \theta \cdot < \epsilon^*$ so that

$$\psi(\theta^* + \theta_1) - \psi(\theta^*) - \theta_1(v + \epsilon) < -\theta_1 \epsilon/2$$

and

$$\overline{\lim}_{n\to\infty} n^{-1} \log P_n^*(n^{-1}S_n > v + \varepsilon) \le -\theta_1 \varepsilon/2 ,$$

which establishes one half of (2.2).

On the other hand, for $0 < \theta < \epsilon^*$.

$$P_n^{\bullet}(n^{-1}S_n < v - \varepsilon) = P_n^{\bullet}(-\theta S_n > -\theta n(v - \varepsilon))$$

$$\leq \exp(\theta n(v - \varepsilon)) E_n^{\bullet} \exp(-\theta S_n) ,$$

where

$$\exp(\theta n(v-\varepsilon)) E_n^* \exp(-\theta S_n) = \exp(\theta n(v-\varepsilon)) \int \exp(-\theta x) P_n^* (S_n \in dx)$$
$$= \exp(\theta n(v-\varepsilon)) \exp(\psi_n(\theta^* - \theta) - \psi_n(\theta^*)) .$$

Hence,

$$\overline{\lim}_{n \to \infty} P_n^*(n^{-1}S_n < v - \varepsilon) \le \theta(v - \varepsilon) + \psi(\theta^* - \theta) - \psi(\theta^*) . \tag{3.2}$$

Then, as before.

$$\psi(\theta^* - \theta) - \psi(\theta^*) - \theta(v - \varepsilon) = -\theta\varepsilon + o(\theta)$$
 as $\theta \to 0$

so that we can choose θ_2 with $0 < \theta_2 < \epsilon^*$ so that

$$\psi(\theta^* - \theta_2) - \psi(\theta^*) + \theta_2(v - \varepsilon) \le -\theta_2 \varepsilon/2$$

and

$$\overline{\lim_{n\to\infty}} n^{-1} \log P_n^*(n^{-1}S_n < v - \varepsilon) \le -\theta_2 \varepsilon/2,$$

which completes the proof for k = 0.

For $k \ge 1$, we first note that $E \exp(\theta(S_n - S_{n-k})) < \infty$ for all $|\theta| < \delta$ for some $\delta > 0$ if condition (1.8) holds. To see this, apply the Cauchy-Schwarz inequality k times to obtain

$$\begin{split} E \exp(\theta(S_n - S_{n-k})) & \leq (E \exp(\theta X_n)^2)^{1/2} E(\exp(\theta(S_{n-1} - S_{n-k})^2)^{1/2} \\ & \leq (E \exp(2\theta X_n))^{1/2} E(\exp(2\theta(S_{n-1} - S_{n-k}))^{1/2} \\ & \leq (E \exp(2\theta X_n))^{1/2} (E \exp(4\theta X_{n-1}))^{1/4} ... (E \exp(2^{k+1}\theta X_{n-k+1}))^{2^{-(k+1)}} \end{split}.$$

We choose n_0 suitably large so that, for some finite M,

$$(Ee^{20X_a})^{1/2}E(e^{40X_{a-1}})^{1/4}...Ee^{2^{t-1}0X_{a-t-1}})^{2^{-(t+1)}} < M$$

for all $n \ge n_0$, which is possible by assumption (1.8).

For $k \ge 1$, we then have

$$P_n^{\bullet}(n^{-1}S_{n-k} > v+\varepsilon) \leq \exp(-\theta n(v+\varepsilon))E_n^{\bullet}\exp(\theta S_{n-k})$$

$$\leq \exp(-\theta n(v+\varepsilon))\int \exp(\theta \sum_{i=1}^{n-k} x_i)\exp(\theta^{\bullet} \sum_{i=1}^{n} x_i - \psi_n(\theta^{\bullet}))P(X_1 \in dx_1, \dots, X_n \in dx_n)$$

$$\leq \exp(-\theta n(v+\varepsilon))E[\exp((\theta + \theta^{\bullet})S_n - \theta(S_n - S_{n-k}) - \psi_n(\theta^{\bullet}))]$$

$$\leq \exp(-\theta n(v+\varepsilon)(E\exp(p(\theta + \theta^{\bullet})S_n))^{1/p}(E\exp(-q\theta(S_n - S_{n-k})))^{1/q}\exp(-\psi_n(\theta^{\bullet}))$$

for positive p and q with $p^{-1}+q^{-1}=1$ by Hölder's inequality. We choose p sufficiently close to 1 and θ sufficiently small so that $p(\theta+\theta^*)$ is within the required neighborhood of θ^* and $q\theta < \delta$, so that $E \exp(-q\theta(S_n-S_{n-k}))^{1/q}$ is bounded for $n \ge n_0$. Hence,

$$\overline{\lim_{n \to \infty}} n^{-1} \log P_n^{\bullet}(n^{-1} S_{n-k} > v + \varepsilon) \le -\theta(v + \varepsilon) + \psi(p(\theta + \theta^{\bullet}))^{1/p} - \psi(\theta^{\bullet}) . \tag{3.3}$$

Since p was arbitrary, we can let $p \to 1$ in (3.3) to obtain the analog of (3.1) with S_{n-k} instead of S_n .

Similarly,

$$P_n^{\circ}(n^{-1}S_{n-k} < v - \varepsilon) \leq \exp(\theta n(v - \varepsilon)) E_n^{\circ} \exp(-\theta S_{n-k})$$

$$\leq \exp(\theta n(v - \varepsilon)) \int \exp(-\theta \sum_{i=1}^{n-k} x_i) \exp(\theta^{\circ} \sum_{i=1}^{n} x_i - \psi_n(\theta^{\circ})) P(X_1 \in dx_1, \dots, X_n \in dx_n)$$

$$\leq \exp(\theta n(v - \varepsilon)) E[\exp(\theta^{\circ} - \theta) S_n + \theta(S_n - S_{n-k}) - \psi_n(\theta^{\circ})]$$

$$\leq \exp(\theta n(v - \varepsilon)) (E \exp(p(\theta^{\circ} - \theta) S_n))^{1/p} (E \exp(q\theta(S_n - S_{n-k})))^{1/q} \exp(-\psi_n(\theta^{\circ}))$$

for positive p and q with $p^{-1} + q^{-1} = 1$ by Hölder's inequality. Reasoning as in (3.3), we obtain

$$\overline{\lim} n^{-1} \log P_n^{\bullet}(n^{-1} S_{n-k} < v - \varepsilon) \le \theta(v - \varepsilon) + \psi(p(\theta^{\bullet} - \theta))^{1/p} - \psi(\theta^{\bullet}) . \tag{3.4}$$

Letting $p \to 1$ in (3.4) we obtain the analog of (3.2) with S_{n-k} instead of S_n . The rest of the proof is the same as for k = 0.

4. Proof of Theorem 4

We construct discrete-time processes satisfying the conditions of Theorem 1 that suitably approximate the continuous-time processes. In particular, for any $\delta > 0$, we construct a discrete-time waiting-time process $\{W_n^{\delta}\}$ by defining service times V_n^{δ} and interarrival times U_n^{δ} via

$$V_n^{\delta} = I((n+1)\delta) - I(n\delta) \quad \text{and} \quad U_n^{\delta} = \delta \,, \, n \ge 1 \,. \tag{4.1}$$

Since $EY(t) = \rho t$ for $\rho < 1$, $EV_n^{\delta} < EU_n^{\delta}$. We initialize by setting $W_0^{\delta} = L(0)$. Then, by induction, we have

$$W_n^{\delta} \le L(n\delta) \le W_n^{\delta} + \delta, n \ge 0. \tag{4.2}$$

Since Y(t) has stationary increments, L(t) is distributed the same as $\sup\{Y(s): 0 \le s \le t\}$. Since this supremum is nondecreasing, $L(t) \Rightarrow L$ as $t \to \infty$. Since $W_n^\delta \Rightarrow W^\delta$ and $L(n\delta) \Rightarrow L$ as $n \to \infty$, we have

$$Ee^{0W^4} \le Ee^{0L} \le e^{08} Ee^{0W^4}$$
 (4.3)

From (4.3), we see that $Ee^{\theta L} < \infty$ if and only if $Ee^{\theta W^{\delta}} < \infty$.

Hence, it suffices to show that $\sup\{\theta: Ee^{\theta W^0} < \infty\} = \theta^*$. For this purpose, let $S_n^\delta = V_0^\delta + ... + V_{n-1}^\delta - n\delta$. Then

$$Ee^{\Theta(S[||x|]-\delta)} = Ee^{\Theta(Y(\delta[||x|])-\delta)} \le Ee^{\ThetaY(t)}$$

$$\le Ee^{\Theta(Y(\delta[||x|]+\delta)} \le Ee^{\Theta(S[||x|]+\delta)}. \tag{4.4}$$

Therefore,

$$\lim_{t \to \infty} t^{-1} \log E e^{\theta S[t/\delta]} \le \lim_{t \to \infty} t^{-1} \log E e^{\theta S[t/\delta]} \le \lim_{t \to \infty} t^{-1} \log E e^{\theta S[t/\delta]}. \tag{4.5}$$

Hence.

$$\lim_{n \to \infty} n^{-1} \log E e^{\theta S_n^{\delta}} = \delta^{-1} \psi(\theta) . \tag{4.6}$$

Since $\delta^{-1}\psi(\theta) = 0$ if and only if $\psi(\theta) = 0$, the proof is complete.

5. Proof of Theorem 5

By Theorem 3.

$$n^{-1}\log Ee^{-\theta S_n^{**}} \rightarrow \psi_n^*(-\theta) = -\psi_A^{-1}(\theta) \text{ as } n \rightarrow \infty$$

for each $\theta > 0$. Now we consider the waiting time and workload in the G/D/1 queue with the given point process as the arrival process. We let the deterministic service times have mean 1 and the arrival processes have rate ρ where $0 < \rho < 1$. This requires that we scale the original process.

By Theorem 1, in the customer-stationary case (1.1) holds for each ρ , $0 < \rho < 1$, where $\theta_{\mathbf{r}}^{*}(\rho)$ satisfies equation (1.30), i.e.,

$$\Psi_{w}(-\theta_{w}^{*}(\rho)/\rho) = -\theta_{w}^{*}(\rho), 0 < \rho < 1.$$
 (5.1)

On the other hand, by Theorem 4 and Proposition 7, in the time-stationary case (1.36) holds for each ρ , $0 < \rho < 1$, where the decay rate $\theta_L^*(\rho)$ satisfies

$$\rho \psi_A(\psi_*(\theta_L^*(\rho))) - \theta_L^*(\rho) = \rho \psi_A(\theta_L^*(\rho)) - \theta_L^*(\rho) = 0, \qquad (5.2)$$

because the decay rate function of $A(\rho t)$ is $\rho \psi_A$. However, by (1.29), (5.2) is equivalent to

$$-\psi_{\mu}^{\circ}(-\theta_{L}^{\circ}(\rho)/\rho) = \psi_{A}^{-1}(\theta_{L}^{\circ}(\rho)/\rho) = \theta_{L}^{\circ}(\rho) , 0 < \rho < 1.$$
 (5.3)

By Proposition 8, $\theta_W^*(\rho) = \theta_L^*(\rho)$ for $0 < \rho < 1$. Hence, (5.3) becomes

$$\psi_w^{\circ}(-\theta_W^{\circ}(\rho)/\rho) = -\theta_W^{\circ}(\rho), 0 < \rho < 1. \tag{5.4}$$

Finally, by Proposition 5, (5.1) and (5.4) imply that $\psi_{ii} = \psi_{ii}^{*}$.

6. Proof of Theorem 6

By Theorem 5, $\psi_{\mu}(-\theta) = -\psi_A^{-1}(\theta)$. Paralleling the proof of Theorem 5, we have

$$\psi_{w}(-\theta_{W}^{\bullet}(\rho)/\rho) = -\psi_{v}(\theta_{W}^{\bullet}(\rho)), 0 < \rho < 1, \tag{6.1}$$

instead of (5.1) and

$$\rho \psi_A(\psi_\nu(\theta_L^*(\rho)) - \theta_L^*(\rho) = 0, 0 < \rho < 1, \tag{6.2}$$

instead of (5.2). However, (6.2) is equivalent to

$$\psi_A^{-1}(\theta_L^{\bullet}(\rho)/\rho) = \psi_{\nu}(\theta_L^{\bullet}(\rho)) , 0 < \rho < 1 .$$
 (6.3)

Since $\psi_A^{-1}(\theta) = -\psi_H(-\theta)$, (6.3) coincides with (6.1), so that we must have $\theta_L^{\bullet}(\rho) = \theta_W^{\bullet}(\rho)$, $0 < \rho < 1$.

7. Proof of Proposition 7

Note that, for any $\varepsilon > 0$, there is an n_0 such that

$$Ee^{\hat{\theta}I(t)} = \sum_{n=0}^{\infty} Ee^{\sum_{i=1}^{n} V_{i}} P(A(t) = n)$$

$$\leq \sum_{n=0}^{\infty} e^{n(\psi_{i}(\hat{\theta}) + \varepsilon)} P(A(t) = n) + Ee^{\hat{\theta} \sum_{i=0}^{\infty} V_{i}}$$

$$\leq Ee^{(\psi_{i}(\hat{\theta}) + \varepsilon)A(t)} + Ee^{\hat{\theta} \sum_{i=0}^{\infty} V_{i}}$$

$$\leq e^{i\psi_{A}(\psi_{i}(\hat{\theta}) + \varepsilon) + \varepsilon} + Ee^{\hat{\theta} \sum_{i=0}^{\infty} V_{i}}$$

for r suitably large. Hence,

$$\overline{\lim}_{t \to 0} t^{-1} \log \mathcal{E} e^{\hat{\theta} I(t)} \le \psi_A(\psi_V(\hat{\theta}) + \varepsilon) + \varepsilon \ .$$

Since ε was arbitrary and ψ_A is continuous at $\psi_{\nu}(\hat{\theta})$.

$$\overline{\lim}_{t \to \infty} t^{-1} \log E e^{\hat{\theta} I(t)} \le \psi_A(\psi_V(\hat{\theta})) .$$

The reasoning for the other direction is essentially the same.

8. Proof of Proposition 9

We shall work with characterization (ii) in Proposition 1. Note that

$$W = \sum_{i=1}^{(Q^a-1)^*} V_i + V_a^a \ge \sum_{i=1}^{(Q^a-1)^*} V_i$$
 (8.1)

and

$$L = \sum_{i=1}^{(Q-1)^*} + V_e \ge \sum_{i=1}^{(Q-1)^*} V_i , \qquad (8.2)$$

where V_a^a and V_a are the equilibrium residual service times of the customer in service (which in general depend upon Q^a and Q). Since the argument is essentially the same for W and L, we henceforth consider only W. To have a useful inequality in the opposite direction, we truncate the service times by setting $V_n^c = \min\{V_n, c\}, n \ge 1$. Then

$$W^c \le \sum_{i=1}^{Q^c} V_i^c + c . \tag{8.3}$$

From (8.1), we obtain

$$Ee^{\Theta W} \geq E(Ee^{\Theta V_1})^{Q^n-1}$$
.

so that $\theta_{Q^*}^* \ge \log E e^{\theta_W^* V_1}$. (As in Proposition 8, we use the fact that $\theta_W^* < \theta_{V_1}^*$.) From (8.3), we obtain

$$Ee^{\theta W'} \leq e^{\theta c} E(Ee^{\theta V_i})^{Q''}$$

so that

Then note that V_1^c , W^c , Q^{ac} , Q^c and L^c increase stochastically to their limits V_1 , W, Q^a , Q and L as $c \to \infty$, see Theorems 4, 5 and 8 plus the remark on p. 216 of Whitt (1981). Hence

$$\theta_{Q^a}^{\bullet} \leq \liminf_{c \to \infty} \theta_{Q^a}^{\bullet} \leq \lim_{c \to \infty} \log Ee^{\theta_w^{\bullet} V_1^{\bullet}} = \log Ee^{\theta_w^{\bullet} V_1} < \infty$$
.

9. An Example

In this section we give an example.

Example 1. To see that the conditions in Theorem 1 are not necessary for (1.1) or (1.2), consider the G/G/1 model with

$$P(U_{2n+1} = 1, U_{2n+2} = 1 + Y_n, V_{2n+1} = 1 + Y_n, V_{2n+2} = 0 \text{ for all } n) = 1/2$$

and

$$P(U_{2n+1} = 1 + Y_n, U_{2n+2} = 1, V_{2n+1} = 0, V_{2n+2} = 1 + Y_{n+1} \text{ for all } n) = 1/2$$

where $\{Y_n\}$ is an i.i.d. sequence of exponential random variables with mean 1. Then $\{U_n, V_n\}$ is stationary with $EV_n = 1 < EU_n = 3/2$, so that $\rho = 2/3$. Moreover, it is easy to see that, for $n \ge 1$,

$$P(W_n > x) = P(W > x) = (1/2)e^{-x}, x > 0$$

but

$$P(S_{2n+1} = Y_n, S_{2n+2} = -n \text{ for all } n)$$

= $P(S_1 = -(n + Y_1), S_{2n+2} = Y_{n+1} - (n + Y_1) \text{ for all } n) = 1/2,$

so that

$$Ee^{\theta S_{2n-1}} = \frac{1}{2} Ee^{\theta Y_1} + \frac{1}{2} Ee^{-\theta (n+Y_1)},$$

$$Ee^{\theta S_{2n-2}} = \frac{1}{2} e^{-\theta n} + \frac{1}{2} Ee^{\theta (Y_{n-1}-n-Y_1)},$$

and

$$n^{-1}\log Ee^{\theta S_n} \to \psi(\theta) = -\theta/2 \text{ as } n \to \infty$$
.

Hence, (1.1) and (1.2) hold, but $\psi(\theta^*) = 0$ for $\theta^* = 0$.

References

- ABATE, J., CHOUDHURY, G. L. and WHITT, W. (1992a) Exponential approximations for tail probabilities of queues, I: waiting times. submitted.
- ABATE, J., CHOUDHURY, G. L. and WHITT, W. (1992b) Exponential approximations for tail probabilities of queues, II: sojourn time and workload. submitted.
- ABATE, J., CHOUDHURY, G. L. and WHITT, W. (1992c) Asymptotics for steady-state tail probabilities in structured Markov chains. submitted.
- ABATE, J., CHOUDHURY, G. L. and WHITT, W. (1992d) Calculation of the GI/G/1 waitingtime distribution and its cumulants from Pollaczek's formulas, submitted.
- ABATE, J. and WHITT, W. (1992) A heavy-traffic expansion for asymptotic decay rates of tail probabilities in multi-channel queues. submitted.
- ADDIE, R. G. and ZUCKERMAN, M. (1993) An approximation for performance evaluation of stationary single server queues. *IEEE Trans. Commun.*, to appear.
- ASMUSSEN, S. (1987) Applied Probability and Queues, Wiley, New York.
- ASMUSSEN, S. (1989) Risk theory in a Markovian environment. Scand. Act. J. 69-100.
- ASMUSSEN, S. and PERRY, D. (1992) On cycle maxima, first passage problems and extreme value theory for queues Stochastic Models, to appear.
- BAIOCCHI, A. (1992) Asymptotic behavior of the loss probability of the MAP/GI/1/K queue, part I: theory. INFOCOM Dept., University of Rome "La Sapienza."
- BOROVKOV, A. A. (1976) Stochastic Processes in Queueing Theory, Springer-Verlag, New York.
- BUCKLEW, J. A. (1990) Large Deviations Techniques in Decision, Simulation and Estimation.

 Wiley, New York.
- CHANG, C.-S. (1992) Stability, queue length and delay, part II: stochastic queueing networks.

 IBM T. J. Watson Research Center, Yorktown Heights, NY.

- CHANG, C.-S., HEIDELBERGER, P., JUNEJA, S. and SHAHABUDDIN, P. (1992) Effective bandwidth and fast simulation of ATM intree networks. IBM T. J. Watson Research Center, Yorktown Heights, NY.
- CHOUDHURY, G. L., LUCANTONI, D. M. and WHITT, W. (1993) Tail probabilities in queues with many independent sources, in preparation.
- CHOUDHURY, G. L. and WHITT, W. (1992) Heavy-traffic asymptotic expansions for the asymptotic decay rates in the BMAP/GI/1 queue. submitted.
- CHUNG, K. L. (1974) A Course in Probability Theory, second ed., Academic Press, New York.
- DEMBO, A. and ZEITOUNI, O. (1992) Large Deviations Techniques and Applications, A. K. Peters, Wellesley, MA.
- ELLIS, R. (1984) Large deviations for a general class of random vectors. Ann. Probab. 12, 1-12.
- ELWALID, A. I. and MITRA, D. (1992) Effective bandwidth of general Markovian traffic sources and admission control of high speed networks. submitted.
- FELLER, W. (1971) An Introduction to Probability Theory and its Applications, Vol. II, second ed., Wiley, New York.
- FRANKEN, P., KÖNIG, D., ARNDT, U. and SCHMIDT, V. (1981) Queues and Point Processes, Akademie-Verlag, Berlin.
- GÄRTNER, J. (1977) On large deviations from the invariant measure. Theor. Probab. Appl. 22, 24-39.
- GIBBENS, R. J. and HUNT, P. J. (1991) Effective bandwidths for the multi-type UAS channel.

 Queueing Systems 9, 17-28.
- GLYNN, P. W. and WHITT, W. (1988a) Ordinary CLT and WLLN versions of $L = \lambda W$. Math. Oper. Res. 13, 674-692.
- GLYNN, P. W. and WHITT, W. (1988b) An LIL version of $L = \lambda W$. Math. Oper. Res. 13. 693-710.

- GLYNN, P. W. and WHITT, W. (1993) Large deviations behavior of counting processes and their inverses. submitted.
- GUERIN, R., AHMADI, H. and NAGHSHINEH, M. (1991) Equivalent capacity and its application to bandwidth application in high-speed networks. *IEEE J. Sel. Areas Commun.*9, 968-981.
- IGLEHART, D. L. and WHITT, W. (1970) Multiple channel queues in heavy-traffic, II: sequences, networks and batches. Adv. Appl. Prob. 2, 355-369.
- IGLEHART, D. L. and WHITT, W. (1971) The equivalence of functional central limit theorems for counting processes and associated partial sums. *Ann. Math. Statist.* 42, 1372-1378.
- KELLY, F. P. (1991) Effective bandwidths at multi-class queues. Queueing Systems 9, 5-16.
- KINGMAN, J. F. C. (1962) On queues in heavy traffic. J. Roy. Stat. Soc., Ser B. 24, 383-392.
- NEUTS, M. F. (1986) The caudal characteristic curve of queues. Adv. Appl. Prob. 18, 221-254.
- SHWARTZ, A. and WEISS, A. (1993) Large Deviations for Performance Analysis: Queues, Communication and Computing, in preparation.
- SOHRABY, K. (1992) On the theory of general on-off sources with applications in high speed networks. IBM T. J. Watson Research Center, Yorktown Heights, NY.
- TAKACS, L. (1962) Introduction to the Theory of Queues, Oxford University Press, New York.
- TAKACS, L. (1963) The limiting distribution of the virtual waiting time and the queue size for a single server queue with recurrer Equat and general service times. Sankhya A25, 91-109.
- TAKACS, L. (1967) Combinatorial Methods in the Theory of Stochastic Processes, Wiley, New York.
- TUMS, H. C. (1986) Stochastic Modeling and analysis: A Computational Approach, Wiley, New York.
- VAN OMMEREN, J. C. W. (1988) Exponential expansion for the tail of the waiting-time probability in the single-server queue with batch arrivals. Adv. Appl. Prob. 20, 880-895.

WHITT, W. (1980) Some useful functions for functional limit theorems. Math. Oper. Res. 5, 67-85.

WHITT, W. (1981) Comparing counting processes and queues. Adv. Appl. Prob. 13, 207-220.

WHITT, W. (1992) Tail probabilities with statistical multiplexing and effective bandwidths for multi-class queues. submitted.